

Command List for DxNet:

SHow/Announce	Announcement list
SHow/Beam <locator>	Show azimut/distance
SHow/BASe or /DATABase	Available Databases on this cluster
SHow/CLuster	Short Cluster configuration
SHow/Configuration	Cluster configuration
SHow/Date	See the current date
SHow/DX	See the 5 last spots
SHow/DX/n [band] [prefix]	See the n last spots (see detailed help: ? SH/DX)
SHow/Filter	See the DX announcement status
SHow/LANGage	Language list
SHow/Prefix <prefix>	Search the DXCC database
SHow/STation <callsign>	Display information for the station call
SHow/Time	Show the current time
SHow/Users	Local cluster configuration
SHow/USERCmd	Display the commands executed at logging
SHow/WWFilter	Show your WW filter status
SHow/WWV	Display WWV propagation information
SET/BEep [d] [a] [t] [l] [w]	Enable BEEP alerts
SET/DX_announcements	Enable the DX announcements
SET/Filter <...>	Enable a DX announcement filter
SET/Here	You're here
SET/NOHere	You're away
SET/HOME <cluster_call>	Set your home cluster
SET/LANGage <num_language>	Set the language (see sh/lang)
SET/LOCator <locator>	Set your locator
SET/LOGIn	Enable login/logout messages
SET/NAME <name>	Set your first name
SET/NOBeep [d] [a] [t] [l] [w]	Disable BEEP alerts
SET/NODX_announcements	Disable the DX announcements
SET/NOFilter	Disable the DX announcement filter
SET/NOLogin	Disable login/logout messages
SET/NOWfilter	Disable the WW announcements feature
SET/QTH <city>	Set your QTH
SET/USERCmd	Set the commands which are executed at login
Announce <msg>	Send a local announcement
Announce/Full <msg>	Send a cluster-wide announcement
Bye (or Quit)	Quit
CONFerence	Enter the local conference
CONFerence/Full	Enter the cluster-wide conference
CONVert/L2C	Convert a locator to coordinates
CONVert/C2L	Convert coordinates to a locator
DX <freq> <dxcall> [comments]	Send a DX spot [freq is in Khz]
EU	Edit user information
Information	Display the informations about the server
Kill <#>	Kill a message
List	Show the new messages
LL <#>	Show the last # messages
LM	Show the whole message addressed to me
LN	Show the new mail messages addressed to me
L> <recipient>	Show all messages addressed to <recipient>
L< <sender>	Show all messages sent by <sender>
LS <title>	Show all message containing <title> in title

Read <#>	Read a message
Send <callsign>[@cluster]	Send a message
Talk [callsign]	Send a break message to [callsign]
WWV <SFI> <A> <K> [comments]	Send a WWV propagation information

Other Help:

Access to Databases:	Enter ? BASE for help on the Databases
Messaging commands:	Enter ? MSG for help on the messaging commands.

You can obtain a detailed help about any command by typing:
? [cmd] (example: ? SH/DX or ? SH for extra help on all SH/xxx)
A command can be shortened by using only the letters shown in capital.

This command displays the list of the #n last spots.
The band and/or the prefix may also be specified.

The default value of (#n) is 5

Example:

SH/DX	(5 last DX spots)
SH/DX/10	(10 last DX spots)
SH/DX 40	(5 last DX spots on the 40m band)
SH/DX 2 PA	(5 last DX spots with PA stations on the 2m band)

For more help contact jimmy at horsezip@usaor.net